Specifications

MODEL	RT-24□-□	RT-100□-□	RT-200□-□									
Rated Voltage	24V DC	100V AC (50/60Hz)	200V AC (50/60Hz)									
Operating Voltage Range	21~27V DC	90~110V AC	180~240V AC									
Rated Power Consumption	Max.24W	Max.32W	Max.30W									
Sound Pressure Level	5.″Rapid Hi−Lo″ at the di	105dB or more e product on the plate of □300mm, an istance of 1m from the center the proc e lower depending on the Sound, usage	duct, in the front direction.									
Volume		adjustable : Min∼Max										
Input Method	Level Hold Input (Sound is played when the CH wire is short-circuited to the COM wire)											
Channel Input	Bit Input (When Sound Group "A" to "G" is selected) Binary Input (When Sound Group "H" is Selected)											
Number of Channels	Bit Input: 8 / Binary Input: 32											
Starting Time	300ms or less (Operation done by both CH signal input or direct power input) CH8(Blue) > CH7(Green) > CH6(Orange) > CH5(Purple) > CH4(Light Green) > CH3(Pink) > CH2(Yellow) > CH1(Sky Blue)											
Channel Input Priority Test Play	CH6(Blue) > CH7(Green) > CH6(Orange	CH1 plays when Select Switch 4										
Flashing Rate	115±30 Flashes Per Minute	105±30 Flashes Per Minute	95±30 Flashes Per Minute									
Bulb	24V 20W (G18/BA15S)		G18/BA15S)									
Luminous Intensity (No Globe)	7,500cd		000cd									
Operating Ambient Temperture	.,	-20°C∼50°C	<u> </u>									
Operating Ambient Humidity	Less than 85%RH (No Condensation)											
Mounting Direction												
Mounting Location		Indoors / Outdoors										
Protection Rating		IP23										
Insulation Resistance	More than 1M	Ω at 500VDC between the terminals a	and the chassis									
Withstand Voltage		petween terminals and chassis without 1000V AC										
Vibration Resistance	30Hz, Back and forth 2h Right and Left 2h Up and down 4h											
Mass (Tolerance±10%)	2.0kg	2.	5kg									
Model Number Configuration	24 100	ted Voltage : 24V DC : 100V AC : 200V AC : E E Type	Dome Color R: Red Y: Yellow G: Green B: Blue									
RT-24A-W18G-1	_3											
	PATL	ITE Corporation										

Specifications

						•									
							,	Sound Li	st						
	01 Bee	(slow intermittent horn)	07	Synthesized	Piano	13	F	ur Elise	19	Mary had a little La	mb 25	Ama	ryllis	31 (Grandfather's Cloc
Atype	02 Stut	ter (rapid intermittent horn)	08	Synthesize	d Bell	14	Maid	en's Prayer	20	The camptown Rad	ces 26				Ave Maria
	03 Bell	(clear highpitched bell)	09	Stutter +		15		Minuet	21	Cuckoo	27		_akeside		
	04 Ye	lp (rapid siren)	10	Synthesized Melod	dy Chime	16	Anı	nie Laurie	22	Blacksmith in the vill	age 28	Mountain	musician	i	
	05	Rapid Hi-Lo	11	Chime	ļ.	17 ∟	ondon b	ridge is falling down	23	On the Avignon brid	dge 29	Romance	De Amour		
	06 N	Melody Chime	12	Call sig	'n	18	Н	oldiridia	24	Daydream Believ	/er 30	Petro	uchka		
			07	Synthesized			Can't Tak	e My Eyes off of You	19			I Don't Want t	o Miss a Thing	31	Imasugu Kisu M
	02 Stut	ter (rapid intermittent horn)	08	Synthesize	d Bell	14	Торс	of the World	20	Rara Sanshai	_		o Mukou	32	Haruyo Koi
Ctype	03 Bell	(clear highpitched bell)		Stutter +					21	Uchuusenkan Yama	ato 27	Aiwa	Katsu		•
	04 Ye	lp (rapid siren)	10	Synthesized Meloc	dy Chime	16	Ama	zing Grace	22		28		uth	İ	
	-	Rapid Hi-Lo	11	Chime	!				23	Makenaide	29	Gatts	udaze	İ	
		Melody Chime	12	Call sig	n	18 L	_es Ch	amps-Elysees	24	Gonna Fly Now(Theme for "Roo	_	Odoru Po	onpokorin	İ	
				Synthesized		13 (Oribia	o Kikinagara	19	Happy Birthda			enlied	31 W	hen the Saints Go Marching I
	02 Stut	ter (rapid intermittent horn)	08	-		-		eptember	20		26		d-nosed Reindeer	32	Londonderry Air
5.	03 Bell	(clear highpitched bell)	09	Chime				ıbino Koibito		I've been working on the Rai			Yellow Ribbon		,
Dtype		lp (rapid siren)		Call sig		16		ino Kehai	22	Bear Song	28	Oh My Darlir	ng Clementine		
		Rapid Hi-Lo	11	Runne				ngoku Sukii Tengoku		Toys Go Cha Cha C			se of Texas		
		Melody Chime	12						24		_		Doodle		
		(slow intermittent horn)		Synthesized		13		ain Ride	19				Laurie	31	Ave Maria
		ter (rapid intermittent horn)	08					ping Hi-Lo	20			London bridge			Grandfather's Cloc
_		(clear highpitched bell)	_	Stutter +		15			21	Alarm Clock		Mary had a			
Etype		lp (rapid siren)						ng Crystals	22			The campt			
		Rapid Hi-Lo	11	Chime				ted Revellie			29		ryllis		
		Melody Chime	12						24		_	Sympho			
	I	Ormino		Oun dig						<u> </u>	- 00	, ~, mpm0	, 110.70		
							So	ound gro	up	S					
		Group A		Group B	Gr	oup	С	Group D		Group E	Gr	oup F	Group	G	Group H
Sound							_								
	roups	¥∎∎∎		¥₽ĦĦ□	V∎			V□□□□		¥□□□□	Ψ		V□□□		
Sound		61234		<u>61234</u>	<u>8</u> 1	2 3 4	1	S1234		S1234	<u>8</u> 1	2 3 4	<u>5123</u>	4	S1234
+\/\	CH1	Fur Elise	Mar	y had a little Lamb	Am	naryl	lis	Grandfather's C	lock	Romance De Amour	Mary ha	d a little Lamb	Beep (slow interm	nittent hor	
	CH2	Maiden's Prayer	The	camptown Races	Symph			Ave Maria	а	The camptown Races	Symph	ony No.40	Stutter (rapid inter	mittent ho	Binary mode
	CH3	Minuet		Cuckoo	Silent	Lake	eside	Daydream Belie		Minuet	Но	ldiridia	Bell (clear highp	itched be	ell)
	CH4	Annie Laurie	Blac	ksmith in the village	Mounta			London bridge is falling	down	Ave Maria		am Believer	Yelp (rapid	d sirer	$\frac{1}{1}$ Sound 1–32
Atype	CH5	London bridge is falling down	On	the Avignon bridge	Romano	e De /	Amour	Bell (clear highpitched	l bell)	Stutter + Bell	Rapi	d Hi-Lo	Rapid H	li-Lo	can be
	CH6	Holdiridia	Day	dream Believer	Petr	oucl	hka	Yelp (rapid sir	en)	Synthesized Melody Chime		dy Chime	Melody (selected by
	CH7	Chime		Chime		hime		Synthesized Pi		Synthesized Piano		sized Piano	Synthesize		using GHI-
	CH8	Call sign		Call sign		ll sig		Synthesized E	Bell	Synthesized Bell	Synth	esized Bell	Synthesiz	ed Be	CH6
	CH1	Can't Take My Eyes off of You		Canon	I Don't Wan			Imasugu Kisu			Beep (slow	intermittent horn)	Odoru Pon	pokor	in
	CH2	Top of the World	Ra		Yozora	ano M	lukou	Haruvo Ko		Makenaide	Stutter (rap	id intermittent horn)	Aiwa K	atsu	Binary mode
	CH3	The Entertainer	Uch	uusenkan Yamato	Aiwa	a Ka	tsu	Uchuusenkan Yan	nato	Gattsudaze	Stutt	er + Bell	Trut		
<u></u>	CH4	Amazing Grace		Oshiete		ruth		Rara Sansh	ain	Top of the World		ed Melody Chime	Les Champs		Sound 1-32
Ctype	CH5	Amairono Kamino Otome	N	Makenaide	Gatt			Can't Take My Eyes off o		Canon	Synthe	sized Piano	Amazing	_	can be
	CH6	Les Champs-Elysees		Fly Now(Theme for "Rocky")	Odoru			Gonna Fly Now(Theme for "R		Haruyo Koi		esized Bell	Yozorano		selected by
	CH7	Chime		Chime		hime		Chime		Chime		hime	Chin		using CHI-
	CH8	Call sign		Call sign		ll sig		Call sign		Call sign		ıll sign	Call s		CH6
	CH1	Runner	HAI	PPY BIRTHDAY	She Wore			Yellow Rose of To		Runner		oku Sukii Tengoku	Doyoubino		to
	CH2	Mamotte Agetai		Ні Но	Oh My Dai			Yankee Doo		Iro Howaitoburendo		ko Irukana	I've been working or		─ Rinary mode
	CH3	Oribiao Kikinagara	I've b	een working on the Railroad	Yellow R			When the Saints Go March		Wiegenlied		Kikinagara	She Wore a Yel	low Ribb	on on
I	CH4	A September	F	Bear Song	Yanke			Londonderry	Air	Hi Ho		Red-nosed Reindeer	Yankee D		Sound 1-32
Dtype	CH5	Doyoubino Koibito		s Go Cha Cha Cha	When the Sa			Beep (slow intermittent		Bell (clear highpitched bell)		d Hi-Lo	Synthesize		can be
	CH6	Akino Kehai		nnako Irukana	Londo			Stutter (rapid intermittent				dy Chime	Synthesize		selected by
	CH7	Saafu Tengoku Sukii Tengoku	_	Viegenlied		unne		Chime	,	Chime		hime	Chin		using CHI-
		Iro Howaitoburendo		oh the Red-nosed Reindeer	Mamot			Call sign		Call sign		ıll sign	Call s		CH6
	CH1	Fur Elise		Minuet		r Elis		Alien Chatt		Train Ride		d Hi-Lo	Beep (slow interm		m)
	CH2	Minuet	Δ	nnie Laurie	London brid			Falling Cryst		Galloping Hi-Lo		hime	Stutter (rapid inter		─ Binary mode.
	CH3	Annie Laurie	$\overline{}$	Amaryllis	Mary had			Inverted Reve		Inverted Revellie		id intermittent horn)	Bell (clear highp		
	CH4	London bridge is falling down	Q.,,	mphony No.40	The cam										Sound 1−32
Etype	CH5	Mary had a little Lamb		ndfather's Clock				Galactic Mo				ng Phone	Yelp (rapid		can be
I						naryl		Ringing Pho				er + Bell	Rapid F		- selected by
	CH6	The camptown Races	_ ′	Ave Maria	Grandfa			Two Tone		Ringing Hi-Lo		ed Melody Chime	Melody (— USING CHI-
	CH7	Chime		Callaign		hime		Alarm Clo			_	sized Piano	Synthesize		10 CH6
	CH8	Call sign	12	Call sign		ll sig	ζN	runging Hi-	∟0	Synthesized Bell	oynth	ssizea Bell	Synthesiz	eu Be	#II
DT 044 1	V100	XFactory defa	ault	setting(grou	JpA)										
RT-24A-W18G-2_3															

PATLITE Corporation

